

Declaration of Conformity to EN 50549-1:2019 With Irish Deviations According to EN50438

Micro-generator details

MICRO-GENERATOR Type reference	GW700-XS	GW1000-XS	GW1500-XS	GW2000-XS	GW2500-XS	GW3000-XS
Maximum continuous rating	700W	1000W	1500W	2000W	2500W	3000W
Manufacturer	JIANGSU GOODWE POWER SUPPLY TECHNOLOGY CO.,LTD.					
Address	No.90 Zijin Rd., New District, Suzhou, 215011, China					
Tel	+86 512 6239 7998					
E-mail address	service@goodwe.com					
Reference standard No.	BS EN 50438:2013,EN 50549-1:2019					
Date	09/23/2020					
SIGNATURE						

Power quality

Harmonic current emission											
	Maximum permissible harmonic current as per EN 61000-3-2, Class A										
	Odd harmonics							Even harmonics			
Harmonic Order n	3	5	7	9	11	13	15≤n≤39	2	4	6	8≤n≤40
Limit	2.30	1.14	0.77	0.4	0.33	0.21	0.15(15/n)	1.08	0.43	0.3	0.23(8/n)
Test value	0.261	0.083	0.019	0.008	0.012	0.011	0.005	0.081	0.043	0.005	0.003

Voltage fluctuations and flicker					
	Maximum permissible flicker and voltage fluctuation as per En 61000-3-3				
Value	P_{st}	P_{lt}	$d(t) - 500ms$	d_c	d_{max}
Limit	1.0	0.65	3.3%	3.3%	4%
Test value	0.12	0.10	0.00%	0.54%	0.61%

Over-/under-frequency tests

	Over-frequency		Under-frequency	
Parameter	Frequency	Disconnection time	Frequency	Disconnection time
Protection limit (FROM Table 4 or Annex A)	50.5Hz	0.5s	48Hz	0.5s
Actual setting (as applied to interface protection)	50.5Hz	0.44s	48Hz	0.44s
Trip value(test result)	50.6Hz	0.230s	48Hz	0.301s

Over-/under-voltage tests (single stage protection)

	Over-voltage		Under-voltage	
Parameter	Voltage	Disconnection time	Voltage	Disconnection time
Protection limit (from Table 4 or Annex A)	253V	0.5s	207V	0.5s
Actual setting (as applied to interface protection)	253V	0.44s	207V	0.44s
Trip value(test result)	254V	0.40s	206V	0.411s

Short-circuit current parameters

Parameter	Symbol	Time after fault	Volts	Amps
Peak short-circuit current	/	20ms	105.35V	3.37A
Initial value of aperiodic component	/	100ms	NA	NA
Initial symmetrical short-circuit current	/	250ms	NA	NA
Decaying (aperiodic) component of short-circuit current	/	500ms	NA	NA
Reactance/Resistance ratio of source	/	Time to trip	4ms	